Crear Horarios y Grupos de Acceso

1.- Ir a Home -> Time Schedules -> Clic ADD y asignarle un nombre al Horario

() = = * * * !	▶ = Ec	lipse 700	Hardware I	Browser Selec	ted Schedules		X
Home Setup	Reports T	ools View	Hardware	Browser Tim	e Schedules		
Add Remove Copy	Add Remove	Download D All S	ownload Selected	Controllers -			
Time Schedules	lime Intervals		Downloads				
Live Events Hardware Setu	p Time Schedules						d þ x
Always	ura			Contraction 2 ↓ 00 Contraction 2 ↓ 00 Contr	a Mode	Horario Autoapertur Yes Scan/Time Intervals	

2.- Clic en Add para crear un intervalo de horas -> y seleccionar días y horas en las que estará activo este nuevo horario creado para la autoapertura.

		da 🕹 🦻		Eclipse 700	Hardw	are Browser	Selected Schedules				x
	Home	Setup	Reports	Tools View	/ Hardv	vare Browser	Time	Schedules			
Add	Remove	Copy	Add Remove	Download All	Download Selected Downlo	P Controlle	rs •				
Live Eve Genera	ents Haro	lware Setup	Time Schedules	s						4	⊳ ×
	) Always Horario Ver	Autoapertu V,TH,F (09:00				E E Bay S M T W T F S	eral tart Time nd Time of Wer elect M-F londay uesday /ednesda hursday iday aturday	ek	er: 09h 00m 11h 00m V Yes V Yes V Yes V Yes V Yes V Yes No		

Clic en Save (Diskette azul arriba de las opciones)

3.- Ir a Setup -> Hardware Setup -> All -> Expandir el Gateway, Controlador y Bus de la puerta deseada que tendrá el horario de Auto apertura.

En las opciones "General" Elegir en el renglón "Auto Unlock Schedule" el horario creado anteriormente.



Clic en Save (Diskette azul arriba de las opciones)

4.- Listo, con esto la puerta que tenga esta función permanecerá abierta en el horario establecido.

	(y )	nemonise clocks	C Device	types	Operators	Application	Conn	nections	Diagnostic	s Cre	dentia	l S	vstem	
	🌊 Lo	ocal Linkage	🔶 Routes	;						Т	ypes	0	ptions	
		Hardware	Event Mor	nitoring	Perm	nissions		Diagnostics			System			
	Live Ev	ents												↓ ×
	Drag a	column header he	ere to group by	that colur	nn.									
	<b>1</b>	I Timestamp (Se ∇	Location	Message				Detail		Cardnum	Card	Imp	First N	Last Na
	2		A	A						=	A	A	A	A
		06/09/2013 10:	New Control	Controlle	Controller Configuration Saved to Flash Mem			AutoSav	e Configu					
		06/09/2013 10:	Puerta Princi	Reader M	lode Change -	Unlocked								
06/09/2013 10: Puerta Princi Door Unlo					ocked By Time	zone								
		06/09/2013 10:	New Control.	Schedule	Schedule Activate Horario Autoaper									